

imer.d

# ES5000 230V 50HZ #AVR

## LONG RUN ENERGY



A petrol generator designed specifically for intensive operations where performance power is demanded by professional user, over an extended period of time.

| Main Features |      | 10 20 |     |
|---------------|------|-------|-----|
| Frequency     | - NA | Hz    | 50  |
| Voltage       |      | V     | 230 |
| Power factor  |      | cos φ | 0.9 |
| Phase         | 101  |       | 1   |
|               |      |       |     |

| Power Rating                |     |     |
|-----------------------------|-----|-----|
| Emergency Standby Power ESP | kVA | 5.1 |
| Emergency Standby Power ESP | kW  | 4.6 |
| Continuous power COP        | kVA | 4.2 |
| Continuous power COP        | kW  | 3.9 |

#### Ratings definition (ISO-8528)

ESP - Emergency Standby Power:

**ESP** - Emergency Standby Power: It is the maximum power available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utility power outage or under test conditions for up to 200 h of operation per year with the maintenance intervals and procedures being carried out as prescribed by the manufacturers. The permissible average power output over 24 h of operation shall not exceed 70 % of the ESP.

**COP** - Continuos Power:

It is defined as being the maximum power which a generating set is capable of delivering continuously for an unlimited number of hours, with the maintenance intervals and procedure being carried out as prescribed by the manufacturers.

| Engine specifications   |                 |            |  |
|-------------------------|-----------------|------------|--|
| Engine Brand            |                 | Honda      |  |
| Model                   | GX270 Recoil    |            |  |
| Engine cooling system   |                 | Air        |  |
| Displacement            | CM <sup>3</sup> | 270        |  |
| Aspiration              |                 | Natural    |  |
| Operating Speed-Nominal | rpm             | 3000       |  |
| Speed governor          |                 | Mechanical |  |
| Fuel                    |                 | Petrol     |  |
| Oil capacity            | I               | 1.1        |  |
| Starting system         |                 | Recoil     |  |
|                         |                 |            |  |



| Alternator Specifications |    |            |
|---------------------------|----|------------|
| Туре                      |    | Brushes    |
| Class                     |    | Н          |
| IP protection             |    | 23         |
| Poles                     |    | 2          |
| Frequency                 | Hz | 50         |
| Voltage tolerance         | %  | 2          |
| Voltage regulation system |    | Electronic |
| Standard AVR              |    | AVR 520    |
|                           |    | 05         |

ant

4

(L) mm

(W) mm

(H) mm

kg

l/h

l/h

h h

dB(A)

dB(A)

Т

729

500

536

61

11

1.66

2.22

6.63

4.95

97

69



**Dimensional data** 

Fuel tank capacity

Fuel consumption at 75% of Load

Fuel consumption at 100% of Load

Running time at 75% of load

Running time at 100% of load

Guaranteed noise level (LWA)

Noise pressure level @ 7 m

Length Width

Height

Dry weight

Autonomy

Noise level

#### COMMANDS:

- · Selector switch: OFF ON
- Starting systems: Recoil
- Fuel Cock



#### **PROTECTIONS STANDARD:**

- Thermal protection
- Oil Guard

#### SOCKET TYPE

| SCHUKO 230V 16A IP54   | 1 |
|------------------------|---|
| 2P+T CEE 230V 16A IP44 | 1 |

### SUPPLEMENTS CONTROL (Available when ordered)

#### Electrical box DPP + HM

Extra Protection with:

- Differential protection 30mA
- Circuit breaker
- Hourmeter



#### **TRANSPORTATION KIT**

- With fix handles
- With folding handles







The information is aligned with the Data file at the time of download. Printed on 07/12/2022 (ID 2492)



